

The Power and Telephone Line Distribution Module can be used to remotely power 8 or 16 emergency telephones using a single power input. The module also provides pass through connections for ordinary tip and ring telephone lines. 8 or 16 telephone lines can be connected to the module.

Part Numbers:

- **8 Zone** = A705-8
- **16 Zone** = A705-16

Key Features:

- Single power input
- Power and tip and ring outputs for 8 or 16 telephones
- Auxiliary 110V power output
- RJ-11 telephone jack inputs
- Quick release connections for all outputs
- Easy wall mounting
- 19" rack mounting capability
- Rugged steel construction

Specifications:

- **Dimensions:** 17.25" H x 12.65" W x 3.5" D
- **Weight**
 - **A705-8:** 13.5 lbs.
 - **A705-16:** 19 lbs.
- **Mounting Centers:** 12.75" H x 11.95" W
- **Material:** 16 ga (0.062") zinc chromate steel
- **Power:** 110-120VAC, 60Hz, 45W
- **Output:** 9-18VDC, 300mA
- **Maximum Distance to Phone:** 1,000' with 22 AWG wire, 2000' with 19 AWG wire
- **Aux AC Output:** 110VAC, fused 1A
- **Operating Temperature:** -40° to 122° F (-40° to 50° C)

