

OCEAN

MATRIX®

Instruction Manual


OMX-PSW6

6x1 Video & Stereo Audio Passive Switcher

Thank you for purchasing this Ocean Matrix component. This unit is designed to give you years of trouble free professional operation for your most demanding applications. It is our goal to develop long term partnerships with our customers through our commitment to exceed their expectations.

For Repair Information or to view the entire Ocean Matrix product line, please visit our web site.

www.oceanmatrix.com



OMX-PSW6

6x1 Video & Stereo Audio Passive Switcher



The **OMX-PSW6** is a high quality Video and Stereo Audio Passive Switcher. This device is designed as a general purpose signal switcher, or to fit the needs of facilities where “signal sniffing” is needed.

The **OMX-PSW6** may also be used as a 1 x 6 assignment switcher where one set of signals can be fed to any of six feeds.

The unit features top grade, high visibility lockout mechanical switches.

SPECIFICATIONS

Video Inputs:	6 Video via BNC connectors, Non terminating (MBB)
Audio Inputs:	12 via RCA connectors (6 per channel)
Outputs:	Video: 1 via BNC connector Audio: Stereo Pair (L, R) via RCA connectors
Switching:	Mechanical, Interlock Lockout
Dimensions:	1.625”H x 8.25”W x 6”D, Steel Housing
Weight:	1.5 Lbs. (without shipping carton)

OCEAN
MATRIX®

800 Kings Highway • Saugerties, NY 12477
A Division of Tower Products, Inc.